

Battery Power Bank Solution 7000W / 10500W

Contact Us >>> Tel: 855-237-2993 Email: Sales@foreseeson.com



- 7000W / 10500W Capacity, 4 of Output 115V /15A, 2 of Output 240V (18A) (Max. 4.4KW output at once)
- Input (Grid (125V), Solar (45V))
- Indoor only, UL battery
- 3 Year Parts replacement by RMA



The Battery Power Bank is a battery powered AC generator that stores electricity for use when and where power from the grid is unavailable: remote, off-grid, emergency and black-out scenarios. The Battery Power Bank stores electricity from solar and wind chargers (DC input), conventional generators, and the grid (AC input).

Battery Power Bank, Mobile AC power for critical equipment where you need it – in a home, office, hospital, school or emergency shelter.

Battery Power Bank access to USB ports and AC outlets for charging cell phones, tablets, other portable devices and home application.

Locking cabinet for indoor security and heavy-duty lockable casters for safe and easy mobility. As a reliable primary or back-up power supply, the Battery Power Bank is safe for indoor use, is non-toxic and does not require ventilation or cooling.



Battery Power Bank Solution

7000W / 10500W

Contact Us >>> Tel: 855-237-2993 Email: Sales@foreseeson.com

SKU	
7000W Battery	F-GPB-07044
10500W Battery	F-GPB-10044
General	
Operating Temperature	-4 to 122 °F -20 to 50 °C
Mounting	Free-standing
Inverter	
Magnum Energy	MS4448pae
Application	On / Off Grid
AC Connections	(4) 115V GFCI sockets for powering devices rated up to 15 Amps
AC Output¹	18 A, 240V AC, 60 Hz
CEC Weighted Efficiency	94%
Battery	
Depth of Discharge²	up to 100%
Round Trip Efficiency	98%
Solar (PV inlet)	
Magnum Energy Charge Controller	PT-100 MPPT
Input Power, Max	2 kW
Charge Current, Max	40 A DC
PV Array Voltage, Operating	187 to 200 V DC
PV Array Voltage, Max Open Circuit)	240 V DC
Other Features	
System Interface	ME-ARC

Notes:

- 1.) When operating from battery, the maximum inverter power is half the battery capacity (kWh/2h).
 - 2.) Max operating conditions. Refer to Warranty for recommended conditions.
- Specifications are typical/nominal. Subject to change without notice.

"All trade names, marks and logos used here belong to the proper owners."

"The Specification and Terms/Conditions of the products and services could be changed from time to time. The Buyer should reconfirm the Specification and Terms/Conditions before the purchasing."

"All documents should be used only for Reference for the business, not for any other purpose."